



SYSTEM COMPONENTS:

LOW FREQUENCY DRIVER:

Cone Kit:	117H-1
Nom. Impedance:	C8R117
Dynamic Test Input V:	8 Ohm
Sweep Frequency Hz:	5
D.C. Resistance Ohms:	30-1200
	5.0 minimum
	6.0 maximum
Gap Gauge:	.051"
Notes:	Aquaplas On Cone
If Not Serviceable,	
Replace With:	116H-3
Visual Change:	Yes
Baffle Modification:	No
Exact Acoustic Replacement:	No. Slightly
	different. Replace both units in a stereo pair.
Additional Parts Currently Available*:	
Dome:	62112
Mounting Gasket:	52671
Trim Gasket:	52316

MID RANGE DRIVER:

Cone Kit:	LE5-12
Nom. Impedance:	C8RLE510
Dynamic Test Input V:	8 Ohm
Sweep Frequency Hz:	4
D.C. Resistance Ohms:	75-3000
	4.9 minimum
	6.1 maximum
Gap Gauge:	.040"
Notes:	
If Not Serviceable,	
Replace With:	Currently Available
Visual Change:	N/A
Baffle Modification:	N/A
Exact Acoustic Replacement:	N/A
Additional Parts Currently Available*:	

MID RANGE DRIVER (Cont'd)

Dome:	51686
Mounting Gasket:	21771
Trim Gasket:	29931
Terminal Board:	53225

HIGH FREQUENCY DRIVER:

Diaphragm Kit:	034
Nom. Impedance:	D8R034
Dynamic Test Input V:	8 Ohm
Sweep Frequency Hz:	2.5
D.C. Resistance Ohms:	200-2000
	5.4 minimum
	6.6 maximum
Gap Gauge:	.031"
Notes:	Test With Network
If Not Serviceable,	
Replace With:	Currently Available
Visual Change:	N/A
Baffle Modification:	N/A
Exact Acoustic Replacement:	N/A
Additional Parts Currently Available*:	
Mounting Gasket:	57754
Screen:	60424
Screen Gasket:	60752

SYSTEM SPECIFICATIONS:

Nominal Impedance:	8 Ohm
Max Recommended	
Amp Power:	200 Watts Per Channel
Crossover Frequencies:	800 Hz, 3700 Hz
Sensitivity:	88dB (1 Watt @ 1 Meter)
Enclosure Dim:	21-3/8" x 13" x 10" D
	543mm x 330mm x 254mm
Shipping Weight:	35 lbs. - 16 kg.
Additional Parts Currently Available*:	
Binding Posts: Red:	56131
Black:	56130

*Other parts may also be available. Check with JBL for details.

JBL Consumer Products, Inc., 80 Crossways Park West, Woodbury, New York 11797

4/94 REV B